



Calhoun: The NPS Institutional Archive
DSpace Repository

Reports and Technical Reports

All Technical Reports Collection

1988-11

Constructing a unitary Hessenberg matrix from spectral data

Gragg, William B.; Ammar, Gregory S.; Reichel, Lother

Monterey, California. Naval Postgraduate School

<http://hdl.handle.net/10945/29778>

This publication is a work of the U.S. Government as defined in Title 17, United States Code, Section 101. Copyright protection is not available for this work in the United States.

Downloaded from NPS Archive: Calhoun



Calhoun is the Naval Postgraduate School's public access digital repository for research materials and institutional publications created by the NPS community. Calhoun is named for Professor of Mathematics Guy K. Calhoun, NPS's first appointed -- and published -- scholarly author.

Dudley Knox Library / Naval Postgraduate School
411 Dyer Road / 1 University Circle
Monterey, California USA 93943

<http://www.nps.edu/library>

NAVAL POSTGRADUATE SCHOOL

Monterey, California



CONSTRUCTING A UNITARY HESSENBERG
MATRIX FROM SPECTRAL DATA

by William Gragg *with others*
Gregory Ammar
Lothar Reichel

November 1988.

Approved for public release; distribution unlimited
Prepared for: Naval Postgraduate School and
National Science Foundation, Washington
D.C. 20550

NAVAL POSTGRADUATE SCHOOL
Department of Mathematics

Rear Admiral R. C. Austin
Superintendent

Harrison Shull
Provost

This report was prepared in conjunction with research conducted for the National Science Foundation and for the Naval Postgraduate School Research Council and funded by the Naval Postgraduate School Research Council. Reproduction of all or part of this report is authorized.

Prepared by:

REPORT DOCUMENTATION PAGE

DUDLEY KNOX LIBRARY
 NAVAL POSTGRADUATE SCHOOL
 MONTEREY CA 93943-5101

1a REPORT SECURITY CLASSIFICATION		1b RESTRICTIVE MARKINGS	
2a SECURITY CLASSIFICATION AUTHORITY		3 DISTRIBUTION/AVAILABILITY OF REPORT	
2b DECLASSIFICATION/DOWNGRADING SCHEDULE		Approved for public release; distribution unlimited	
3a PERFORMING ORGANIZATION REPORT NUMBER(S) NS-53-89-005		5 MONITORING ORGANIZATION REPORT NUMBER(S) NPS-53-89-005	
6a NAME OF PERFORMING ORGANIZATION Naval Postgraduate School	6b OFFICE SYMBOL (if applicable) 53	7a NAME OF MONITORING ORGANIZATION Naval Postgraduate School and the National Science Foundation	
6c ADDRESS (City, State, and ZIP Code) Monterey, CA 93943		7b ADDRESS (City, State, and ZIP Code) Monterey, CA 93943 and Washington, D.C.	
8a NAME OF FUNDING/SPONSORING ORGANIZATION Naval Postgraduate School	8b OFFICE SYMBOL (if applicable) 53	9 PROCUREMENT INSTRUMENT IDENTIFICATION NUMBER O&MN, Direct funding	
6c ADDRESS (City, State, and ZIP Code) Monterey, CA 93943		10 SOURCE OF FUNDING NUMBERS	
		PROGRAM ELEMENT NO	PROJECT NO
		TASK NO	WORK UNIT ACCESSION NO

11 (Include Security Classification)
 Constructing a Unitary Hessenberg Matrix From Spectral Data

PERSONAL AUTHOR(S)
 William Gragg, Gregory Ammar, Lothar Reichel

12 TYPE OF REPORT Technical Report	13b TIME COVERED FROM 10/1/87 TO 9/39/88	14 DATE OF REPORT (year, Month, Day) 15 November 1988	15 PAGE COUNT 11
---------------------------------------	---	--	---------------------

16 SUPPLEMENTARY NOTATION

COSATI CODES			18 SUBJECT TERMS (Continue on reverse if necessary and identify by block number)
FIELD	GROUP	SUB-GROUP	
			inverse eigenvalue problem, unitary matrix, orthogonal polynomial

19 ABSTRACT (Continue on reverse if necessary and identify by block number)

We consider the numerical construction of a unitary Hessenberg matrix from spectral data using an inverse QR algorithm. Any unitary upper Hessenberg matrix H with nonnegative subdiagonal elements can be represented by $2n - 1$ real parameters. This representation, which we refer to as the *Schur parameterization* of H , facilitates the development of efficient algorithms for this class of matrices. We show that a unitary upper Hessenberg matrix H with positive subdiagonal elements is determined by its eigenvalues and the eigenvalues of a rank-one unitary perturbation of H . The eigenvalues of the perturbation strictly interlace the eigenvalues of H on the unit circle.

20 DISTRIBUTION/AVAILABILITY OF ABSTRACT UNCLASSIFIED/UNLIMITED <input type="checkbox"/> SAME AS RPT <input type="checkbox"/> DTIC USERS <input type="checkbox"/>		21 ABSTRACT SECURITY CLASSIFICATION UNCLASSIFIED	
NAME OF RESPONSIBLE INDIVIDUAL William Gragg		22b TELEPHONE (include Area Code) (408) 646-2194	22c OFFICE SYMBOL 53Gr

Constructing a Unitary Hessenberg Matrix from Spectral Data

Gregory Ammar¹, William Gragg², Lotliar Reichel³

In memory of Peter Henrici

Abstract

We consider the numerical construction of a unitary Hessenberg matrix from spectral data using an inverse QR algorithm. Any unitary upper Hessenberg matrix H with nonnegative subdiagonal elements can be represented by $2n - 1$ real parameters. This representation, which we refer to as the *Schur parameterization* of H , facilitates the development of efficient algorithms for this class of matrices. We show that a unitary upper Hessenberg matrix H with positive subdiagonal elements is determined by its eigenvalues and the eigenvalues of a rank-one unitary perturbation of H . The eigenvalues of the perturbation strictly interlace the eigenvalues of H on the unit circle.

AMS(MOS) Subject Classification: 15A18, 65F15.

Keywords: inverse eigenvalue problem, unitary matrix, orthogonal polynomial.

Presented at the NATO Advanced Study Institute on Numerical Linear Algebra, Digital Signal Processing, and Parallel Algorithms, Leuven, Belgium, August, 1988. This research was supported in part by the National Science Foundation under grant DMS-8704196, and by the Naval Postgraduate School Research Council

¹ Northern Illinois University, Department of Mathematical Sciences, DeKalb, IL 60115, USA

² Naval Postgraduate School, Department of Mathematics, Monterey, CA 93943, USA, on leave from University of Kentucky, Department of Mathematics, Lexington, KY 40506, USA

³ Bergen Scientific Centre IBM, Allégaten 36, N-5007 Bergen, Norway, on leave from University of Kentucky, Department of Mathematics, Lexington, KY 40506, USA

1. Introduction

In this paper we focus on an inverse eigenvalue problem for unitary Hessenberg matrices with positive subdiagonal elements. Throughout this paper all Hessenberg matrices are *upper* Hessenberg matrices. This class of matrices bears many similarities with the class of Jacobi matrices, i.e. real symmetric tridiagonal matrices with positive subdiagonal elements. Any matrix in either class is normal and has distinct eigenvalues. Both $n \times n$ Jacobi matrices and $n \times n$ unitary Hessenberg matrices with positive subdiagonal elements can be parameterized by $2n - 1$ real parameters. This is obvious for Jacobi matrices; for unitary Hessenberg matrices this parameterization is described below. Since unitary Hessenberg matrices with positive subdiagonal elements are determined by $O(n)$ parameters, one can develop efficient algorithms for this class of matrices. These algorithms are analogous with algorithms for Jacobi matrices. For example, the unitary QR algorithm, described in [Gr2], has many similarities with the QR algorithm for Jacobi matrices. Another example is provided by the divide-and-conquer methods that have been developed for both the tridiagonal and unitary eigenproblems [Cu], [DS], [GR1], [GR2].

In this paper we show another analogy of unitary Hessenberg matrices with Jacobi matrices, namely, that a unitary Hessenberg matrix H with positive subdiagonal elements is uniquely determined by its eigenvalues and the eigenvalues of a unitary rank-one perturbation of H . The matrix H can be constructed using $O(n^2)$ arithmetic operations using an inverse unitary QR algorithm. Similar results for Jacobi matrices are well-established [BG1], [BG2], [GH]. The inverse unitary QR algorithm is analogous with the algorithm described in [GH] for Jacobi matrices.

2. Unitary Hessenberg Matrices and Szegő Polynomials

We refer to a *finite Schur parameter sequence* of length n as a sequence of complex numbers $\{\gamma_j\}_{j=1}^n$ with $|\gamma_j| < 1$ for $1 \leq j < n$ and $|\gamma_n| = 1$. Also define the *complementary Schur parameters* $\{\sigma_j\}_{j=1}^{n-1}$ by $\sigma_j := \sqrt{1 - |\gamma_j|^2}$. Associated with the finite Schur parameter sequence $\{\lambda_j\}_{j=1}^n$ is a unitary Hessenberg matrix H with *positive* subdiagonal elements

$$H = H(\gamma_1, \dots, \gamma_{n-1}, \gamma_n) := G_1(\gamma_1)G_2(\gamma_2) \dots G_{n-1}(\gamma_{n-1})\tilde{G}_n(\gamma_n), \quad (2.1)$$

where the Givens reflector $G_j(\gamma_j)$ is the identity matrix of appropriate size except for the 2×2 principal submatrix

$$G_j \begin{bmatrix} j & j+1 \\ j & j+1 \end{bmatrix} = \begin{bmatrix} -\gamma_j & \sigma_j \\ \sigma_j & \bar{\gamma}_j \end{bmatrix},$$

with the bar denoting complex conjugation. The matrix on the right in the product (2.1) is defined by $\tilde{G}_n(\gamma_n) := \text{diag}[1, 1, \dots, 1, -\gamma_n]$. The nonzero entries of $H = [\eta_{j,k}]_{j,k=1}^n$ are then given by $\eta_{j+1,j} := \sigma_j$ and $\eta_{j,k} := -\bar{\gamma}_{j-1}\sigma_j\sigma_{j+1} \dots \sigma_{k-1}\gamma_k$ for $1 \leq j \leq k$, where $\gamma_0 := 1$.

It is easy to see that every $n \times n$ unitary Hessenberg matrix $H = [\eta_{j,k}]_{j,k=1}^n$ with $\eta_{j+1,j} > 0$ is uniquely determined by a finite Schur parameter sequence of length n . In fact, the Schur parameters $\{\gamma_j\}_{j=1}^n$ and the complementary Schur parameters $\{\sigma_j\}_{j=1}^{n-1}$ can be determined from H by

$$\sigma_j = \eta_{j+1,j}, \quad 1 \leq j < n; \quad \gamma_j = -\eta_{1,j}/\sigma_1\sigma_2 \dots \sigma_{j-1}, \quad 1 \leq j \leq n.$$

Hence, we have a one-to-one correspondence between Schur parameter sequences of length n and $n \times n$ unitary Hessenberg matrices with positive subdiagonal elements. This *Schur parameterization of unitary Hessenberg matrices* with positive subdiagonal elements shows that these matrices are determined by $2n - 1$ real parameters: the real and imaginary parts of γ_j for $1 \leq j < n$, and the

argument of γ_n . To avoid numerical instability, however, we also retain the complementary Schur parameters.

Let $H = H_n := H(\gamma_1, \dots, \gamma_{n-1}, \gamma_n)$, and let $H_k := G_1(\gamma_1)G_2(\gamma_2) \dots G_{k-1}(\gamma_{k-1})\tilde{G}_k(\gamma_k)$ be the leading principal submatrix of $H = H_n$ of order k . Introduce the functions

$$\begin{aligned}\phi_k(\lambda) &:= e_1^T(\lambda I - H_k)^{-1}e_1, \\ \psi_k(\lambda) &:= \det(\lambda I - H_k), \\ \pi_k(\lambda) &:= \det(\lambda I - H_{k-1}''').\end{aligned}$$

where $e_1 := [1, 0, \dots, 0]^T$, and H_{k-1}''' denotes the trailing principal submatrix of H_k of order $k-1$. Thus, $\phi_k(\lambda) = \pi_k(\lambda)/\psi_k(\lambda)$. The following proposition can be verified by induction.

Proposition 2.1. The polynomials $\psi_k(\lambda)$ and $\pi_k(\lambda)$, $k > 0$, satisfy

$$\begin{bmatrix} \psi_k(\lambda) & \pi_k(\lambda) \\ \tilde{\psi}_k(\lambda) & \tilde{\pi}_k(\lambda) \end{bmatrix} = \begin{bmatrix} \lambda & \gamma_k \\ \tilde{\gamma}_k \lambda & 1 \end{bmatrix} \begin{bmatrix} \psi_{k-1}(\lambda) & \pi_{k-1}(\lambda) \\ \tilde{\psi}_{k-1}(\lambda) & \tilde{\pi}_{k-1}(\lambda) \end{bmatrix}; \quad \begin{bmatrix} \psi_0(\lambda) & \pi_0(\lambda) \\ \tilde{\psi}_0(\lambda) & \tilde{\pi}_0(\lambda) \end{bmatrix} = \begin{bmatrix} 1 & 1/\lambda \\ 1 & 0 \end{bmatrix}.$$

It follows that for each k , the polynomials $\tilde{\psi}_k(\lambda) := \lambda^k \tilde{\psi}_k(1/\lambda)$ are obtained by reversing and conjugating the coefficients of $\psi_k(\lambda)$. From the initial conditions we recognize $\psi_k(\lambda)$ to be the k th Szegő polynomial determined by the Schur parameter sequence $\{\gamma_j\}_{j=1}^n$. \square

The Szegő polynomials $\{\psi_k\}_{k=0}^n$ are orthogonal with respect to a discrete measure on the unit circle. This measure assigns a positive weight ω_k to each zero λ_k of $\psi_n(\lambda)$. These weights are the numerators in the partial fraction decomposition

$$\phi_n(\lambda) =: \sum_{k=1}^n \frac{\omega_k}{\lambda - \lambda_k},$$

see [Gr1] for details.

Let $H = U\Lambda U^*$, with $\Lambda = \text{diag}[\lambda_1, \lambda_2, \dots, \lambda_n]$ and U unitary, be the spectral resolution of $H = H(\gamma_1, \dots, \gamma_{n-1}, \gamma_n)$, where $*$ denotes transposition and complex conjugation. Let $u := U^T \epsilon_1$ be the vector containing the first components of the eigenvectors of H . Since H has nonzero sub-diagonal elements, every entry of $u = [v_1, v_2, \dots, v_n]^T$ is nonzero, and we normalize U so that each $v_k > 0$. Then

$$\phi_n(\lambda) = u^*(\lambda I - \Lambda)^{-1}u = \sum_{k=1}^n \frac{v_k^2}{\lambda - \lambda_k}.$$

Hence, the weights $\omega_k = v_k^2$ are guaranteed to be positive, and $\sum_{k=1}^n \omega_k = 1$.

3. The Inverse Unitary QR Algorithm

Given n distinct unimodular complex numbers $\{\lambda_k\}_{k=1}^n$ and associated positive weights $\{v_k^2\}_{k=1}^n$, we can construct a unitary Hessenberg matrix H with the λ_k and v_k equal to the eigenvalues and first components of the corresponding eigenvectors of H , respectively. This construction is achieved using an inverse QR algorithm, which is analogous with the procedure of [GH] for real symmetric tridiagonal matrices.

The required Hessenberg matrix is obtained by performing a sequence of elementary unitary similarity transformations to transform the matrix $\begin{bmatrix} \delta & u^* \\ u & \Lambda \end{bmatrix}$ to a Hessenberg matrix $\begin{bmatrix} \delta & c_1^* \\ c_1 & H \end{bmatrix}$ without

using or changing the arbitrary entry δ . Then $H = H(\gamma_1, \dots, \gamma_{n-1}, \gamma_n)$ has the desired eigenvalues and associated eigenvectors.

The idea is to build the Hessenberg matrix by adding weight-abscissa pairs one at a time. Suppose that we have constructed the unitary Hessenberg matrix $H_m := H(\gamma_1, \dots, \gamma_{m-1}, \gamma_m)$, for some $m < n$, corresponding with the weight-abscissa pairs $\{(\omega_k, \lambda_k)\}_{k=1}^m$. Let $\sigma_0 := (\sum_{k=1}^m \omega_k)^{1/2}$ and assume that the first components of the eigenvectors of H_m are $\{(v_k/\sigma_0)\}_{k=1}^m$. In order to add the weight-abscissa pair (v^2, λ) and construct the corresponding $(m+1) \times (m+1)$ unitary Hessenberg matrix $H'_{m+1} := H(\lambda'_1, \lambda'_2, \dots, \lambda'_{m+1})$, we perform a sequence of unitary similarity transformations to put the $(m+2) \times (m+2)$ matrix

$$\tilde{H}^{(1)} := \begin{bmatrix} \delta & v & \sigma_0 \epsilon_1^* \\ v & \lambda & 0^* \\ \sigma_0 \epsilon_1 & 0 & H_m \end{bmatrix} = \begin{bmatrix} \delta & v & \sigma_0 & & & & \\ v & \lambda & & & & & \\ \sigma_0 & & \times & \times & \times & \times & \times \\ & & \times & \times & \times & \times & \times \\ & & & \times & \times & \times & \times \\ & & & & \times & \times & \times \\ & & & & & \times & \times \end{bmatrix}$$

into Hessenberg form without changing δ . Let $\sigma'_0 := \sqrt{\sigma_0^2 + v^2}$ and $\alpha_0 := -v/\sigma'_0$. Then

$$G_2(\alpha_0)\tilde{H}^{(1)} =: \tilde{H}^{(2)} = \begin{bmatrix} \delta & v & \sigma_0 & & & & \\ \sigma'_0 & \times & \times & \times & \times & \times & \times \\ 0 & \times & \times & \times & \times & \times & \times \\ & & \times & \times & \times & \times & \times \\ & & & \times & \times & \times & \times \\ & & & & \times & \times & \times \\ & & & & & \times & \times \end{bmatrix}$$

is a Hessenberg matrix with a trailing principal $(m+1) \times (m+1)$ submatrix, which is both unitary and of Hessenberg form. On the completion of the similarity transformation of $\tilde{H}^{(1)}$, we obtain

$$\tilde{H}^{(2)}G_2^*(\alpha_0) = \begin{bmatrix} \delta & \sigma'_0 & & & & & \\ \sigma'_0 & \times & \times & \times & \times & \times & \times \\ & \otimes & \times & \times & \times & \times & \times \\ & & & \times & \times & \times & \times \\ & & & & \times & \times & \times \\ & & & & & \times & \times \end{bmatrix}. \quad (3.1)$$

The circled element in (3.1) forms a “bulge”, which is to be chased down along the subdiagonal in order to obtain a matrix of Hessenberg form. Define $G_3(\alpha_1)$ so that $G_3(\alpha_1)\tilde{H}^{(2)}G_2^*(\alpha_0) =: \tilde{H}^{(3)}$ is a Hessenberg matrix. Then $\tilde{H}^{(3)}G_3^*(\alpha_1)$ has a bulge, which we annihilate by multiplying from the left with $G_4(\alpha_2)$. Proceeding in this manner, we ultimately chase the bulge off the bottom of the matrix, and obtain the Hessenberg matrix $\tilde{H}^{(m-1)}G_{m-1}^*(\gamma_{m-3})$, which is unitarily similar to $\tilde{H}^{(1)}$. The trailing principal $(m+1) \times (m+1)$ submatrix of $\tilde{H}^{(m-1)}G_{m-1}^*(\gamma_{m-3})$ is unitarily similar to a unitary Hessenberg matrix with positive subdiagonal elements. The latter matrix is the desired Hessenberg matrix $H'_{m+1} = H(\gamma'_1, \gamma'_2, \dots, \gamma'_{m+1})$.

This procedure for adding a weight-abscissa pair to H_m , if implemented by directly manipulating the elements of the matrices $\tilde{H}^{(k)}$, for $1 \leq k < m$, would require $O(m^2)$ arithmetic operations. However,

we note that for each k the trailing $(m+1) \times (m+1)$ principal submatrix of $\tilde{H}^{(k)}$ is unitary and of Hessenberg form, and, therefore, is unitarily similar to a unitary Hessenberg matrix, denoted by $\hat{H}_{m+1}^{(k)}$, with positive subdiagonal elements. Hence, we can carry out the similarity transformations by manipulating the Schur parameters of the matrices $\hat{H}_{m+1}^{(k+2)} = H(\gamma'_1, \gamma'_2, \dots, \gamma'_k, \bar{\lambda}^k \alpha_k, \gamma_{k+1}, \dots, \gamma_m)$. This gives rise to a method that requires only $O(m)$ arithmetic operations in order to add a weight-abscissa pair to H_m . We refer to this method as the *inverse unitary QR algorithm* because of its relationship with the unitary QR algorithm presented in [Gr2].

Inverse Unitary QR Algorithm: adding a weight-abscissa pair (v^2, λ) , where $|\lambda| = 1$, $v > 0$.

$$\sigma'_0 := \sqrt{\sigma_0^2 + v^2};$$

$$\alpha_0 := -v/\sigma'_0; \quad \beta_0 := \sigma_0/\sigma'_0;$$

for $k := 1, 2, \dots, m$

$$\left[\begin{array}{l} \sigma'_k := \beta_{k-1} \sqrt{\sigma_k^2 + |\alpha_{k-1} + \gamma_k \lambda^{k-2} \bar{\alpha}_{k-1}|^2}; \\ \alpha_k := \beta_{k-1} \lambda (\alpha_{k-1} + \gamma_k \lambda^{k-2} \bar{\alpha}_{k-1}) / \sigma'_k; \\ \beta_k := \beta_{k-1} \sigma_k / \sigma'_k; \\ \gamma'_k := \beta_{k-1}^2 \gamma_k - \bar{\lambda}^{k-2} \alpha_{k-1}^2; \\ \gamma'_{m+1} := \lambda \gamma_m; \end{array} \right.$$

□

Thus, the inverse unitary QR algorithm can be used to construct the unitary $n \times n$ Hessenberg matrix $H = H(\gamma_1, \dots, \gamma_{n-1}, \gamma_n)$ from its eigenvalues and the first components of its normalized eigenvectors in $O(n^2)$ arithmetic operations.

4. An Inverse Spectral Problem

Let $H = H(\gamma_1, \dots, \gamma_{n-1}, \gamma_n)$ and $\phi_n(\lambda) = \frac{\pi_n(\lambda)}{\psi_n(\lambda)} = \sum_{k=1}^n \frac{\omega_k}{\lambda - \lambda_k}$. Let $\alpha := e^{i\tau}$ for some $0 < \tau < 2\pi$,

and consider the polynomials

$$\lambda_k(\lambda) := (1 - \alpha)\lambda\pi_k(\lambda) + \alpha\psi_k(\lambda), \quad 0 \leq k \leq n. \quad (4.1)$$

Proposition 4.1. The polynomials $\{\chi_k(\lambda)\}_{k=0}^n$ are the monic Szegő polynomials corresponding with the Schur sequence $\{\alpha\gamma_k\}_{k=1}^n$.

Proof. The definition (4.1) and Proposition 2.1 yield

$$\begin{bmatrix} \chi_k(\lambda) \\ \xi_k(\lambda) \end{bmatrix} = \begin{bmatrix} \lambda & \gamma_k \\ \bar{\gamma}_k \lambda & 1 \end{bmatrix} \begin{bmatrix} \chi_{k-1}(\lambda) \\ \xi_{k-1}(\lambda) \end{bmatrix}, \quad \begin{bmatrix} \chi_0(\lambda) \\ \xi_0(\lambda) \end{bmatrix} = \begin{bmatrix} 1 \\ \alpha \end{bmatrix},$$

where $\xi_k(\lambda) := (1 - \alpha)\lambda\bar{\pi}_k(\lambda) + \alpha\bar{\psi}_k(\lambda)$. On setting $\tilde{\chi}_k(\lambda) = \bar{\alpha}\xi_k(\lambda)$, we obtain

$$\begin{bmatrix} \chi_k(\lambda) \\ \tilde{\chi}_k(\lambda) \end{bmatrix} = \begin{bmatrix} \lambda & \alpha\gamma_k \\ \bar{\alpha}\bar{\gamma}_k\lambda & 1 \end{bmatrix} \begin{bmatrix} \chi_{k-1}(\lambda) \\ \tilde{\chi}_{k-1}(\lambda) \end{bmatrix}, \quad \begin{bmatrix} \chi_0(\lambda) \\ \tilde{\chi}_0(\lambda) \end{bmatrix} = \begin{bmatrix} 1 \\ 1 \end{bmatrix}.$$

□

An immediate consequence of Proposition 4.1 is that each zero of $\chi_n(\lambda)$ has unit modulus. When $\alpha = -1$ the polynomials $\{\chi_k(\lambda)\}_{k=0}^n$ are known as the Szegő polynomials of the second kind corresponding with $\{\gamma_k\}_{k=1}^n$.

Proposition 4.2. The zeros $\{\mu_k\}_{k=0}^n$ of $\chi_n(\lambda)$ strictly interlace the zeros $\{\lambda_k\}_{k=0}^n$ of $\psi_n(\lambda)$ on the unit circle. Moreover, $\prod_{k=1}^n (\mu_k/\lambda_k) = \alpha$.

Proof. Let $\lambda := e^{i\theta}$ for some $0 \leq \theta < 2\pi$, and let $\alpha := e^{i\tau}$ for some $0 < \tau < 2\pi$. Then

$$\begin{aligned}\Phi_n(\lambda) &:= \frac{\chi_n(\lambda)}{\psi_n(\lambda)} = \sum_{k=1}^n \omega_k \frac{\lambda - \alpha\lambda_k}{\lambda - \lambda_k} \\ &= \sum_{k=1}^n \omega_k \frac{1 - \lambda\bar{\lambda}_k + \alpha(1 - \bar{\lambda}\lambda_k)}{|\lambda - \lambda_k|^2} \\ &= \sum_{k=1}^n 2e^{i\tau/2}\omega_k \frac{\operatorname{Re}(e^{i\tau/2}(1 - \bar{\lambda}\lambda_k))}{|\lambda - \lambda_k|^2}.\end{aligned}$$

Thus, $\operatorname{Im}(e^{-i\tau/2}\Phi_n(e^{i\theta})) \equiv 0$ for $0 \leq \theta < 2\pi$. Let $\lambda_k =: e^{i\theta_k}$. We may assume that $0 \leq \theta_1 < \theta_2 < \dots < \theta_n < 2\pi$. Then

$$\begin{aligned}e^{-i\tau/2}\Phi_n(e^{i\theta}) &= \sum_{k=1}^n 2\omega_k \frac{\cos(\tau/2) - \cos(\tau/2 + \theta_k - \theta)}{(1 - \cos(\theta_k - \theta))^2 + \sin^2(\theta_k - \theta)} \\ &= \sum_{k=1}^n \omega_k \frac{\cos(\tau/2) - \cos(\tau/2)\cos(\theta_k - \theta) + \sin(\tau/2)\sin(\theta_k - \theta)}{1 - \cos(\theta_k - \theta)} \\ &= \sum_{k=1}^n \omega_k (\cos(\tau/2) + \sin(\tau/2)\cot((\theta_k - \theta)/2)).\end{aligned}$$

From $0 < \tau < 2\pi$ and $\omega_k > 0$ for all k , it follows that

$$e^{-i\tau/2} \frac{d}{d\theta} \Phi_n(e^{i\theta}) = \frac{1}{2} \sin(\tau/2) \sum_{k=1}^n \omega_k / \sin^2((\theta_k - \theta)/2) > 0 \quad \text{for } \theta \neq \theta_k, 1 \leq k \leq n.$$

Thus, $\Phi_n(e^{i\theta}) \rightarrow -\infty$ as $\theta \searrow \theta_k$, and $\Phi_n(e^{i\theta}) \rightarrow \infty$ as $\theta \nearrow \theta_{k+1}$. This shows that $\theta \rightarrow \Phi_n(e^{i\theta})$ has precisely one zero in $] \theta_k, \theta_{k+1} [$. Consequently, the zeros μ_j of $\Phi_n(\lambda)$ strictly interlace the λ_j on the unit circle. The second statement of the Proposition follows from the fact that $\chi_n(0)/\psi_n(0) = \alpha$. \square

Let $\lambda_k =: e^{i\theta_k}$ and $\mu_k =: e^{i\nu_k}$ for $0 \leq \theta_k, \nu_k < 2\pi$. Then we have $\sum_{k=1}^n (\nu_k - \theta_k) = \tau$. We may assume that the arguments have been ordered so that

$$0 \leq \theta_1 < \nu_1 < \theta_2 < \dots < \nu_{n-1} < \theta_n < \nu_n < \theta_1 + 2\pi. \quad (4.2)$$

Proposition 4.3. With the above notation, and the ordering (4.2), the weights ω_k are given by

$$\omega_k = \frac{1}{\sin(\tau/2)} \frac{\prod_{j=1}^n \sin((\nu_j - \theta_k)/2)}{\prod_{\substack{j=1 \\ j \neq k}}^n \sin((\theta_j - \theta_k)/2)}.$$

Proof. We have

$$(1 - \alpha)\lambda_k\omega_k = \lim_{\lambda \rightarrow \lambda_k} (\lambda - \lambda_k) \frac{\chi_n(\lambda)}{\psi_n(\lambda)} = \frac{\chi_n(\lambda_k)}{\psi_n'(\lambda_k)} = \frac{\prod_{j=1}^n (\lambda_k - \mu_j)}{\prod_{\substack{j=1 \\ j \neq k}}^n (\lambda_k - \lambda_j)}$$

since $\chi_n(\lambda)$ and $\psi_n(\lambda)$ are monic. Thus,

$$(1 - \alpha)\omega_k = e^{-i\theta_k} \frac{\prod_{\substack{j=1 \\ j \neq k}}^n (e^{i\theta_k} - e^{i\nu_j})}{\prod_{\substack{j=1 \\ j \neq k}}^n (e^{i\theta_k} - e^{i\theta_j})} = \frac{\prod_{j=1}^n (1 - e^{i(\nu_j - \theta_k)})}{\prod_{\substack{j=1 \\ j \neq k}}^n (1 - e^{i(\theta_j - \theta_k)})} = -2i\epsilon^{i\tau/2} \frac{\prod_{j=1}^n \sin((\nu_j - \theta_k)/2)}{\prod_{\substack{j=1 \\ j \neq k}}^n \sin((\theta_j - \theta_k)/2)}, \quad (4.3)$$

because

$$1 - e^{i\beta} = -2i \sin(\beta/2), \quad (4.4)$$

and $\sum_{j=1}^n (\nu_j - \theta_j) = \tau$. The formula for the weights now follows by substituting (4.4) with $\beta := \tau$ into (4.3). \square

We can now state the inverse spectral problem and its solution.

Problem: Given two sets of n mutually interlacing points on the unit circle $\{\lambda_k\}_{k=1}^n$ and $\{\mu_k\}_{k=1}^n$, determine the unique unitary Hessenberg matrix $H = H(\gamma_1, \dots, \gamma_{n-1}, \gamma_n)$ and $|\alpha| = 1$ such that the spectrum of H is $\{\lambda_k\}_{k=1}^n$ and the spectrum of $H(\alpha\gamma_1, \dots, \alpha\gamma_{n-1}, \alpha\gamma_n)$ is $\{\mu_k\}_{k=1}^n$.

Solution: Let $\alpha := \prod_{k=1}^n (\mu_k/\lambda_k)$, calculate the weights by Proposition 4.3, and use the inverse unitary QR algorithm to construct $H = H(\gamma_1, \dots, \gamma_{n-1}, \gamma_n)$.

References

- [BG1] D. Boley and G.H. Golub, *Inverse Eigenvalue Problems for Band Matrices*, in Lecture Notes in Mathematics 630, Numerical Analysis, Proceedings of the Biennial Conference Held at Dundee, 1977, G.A. Watson, ed., Springer-Verlag, New York, 1978, pp. 23-31.
- [BG2] D. Boley and G.H. Golub, *A Survey of Matrix Inverse Eigenvalue Problems*, Inverse Problems 3, (1987) 595-622.
- [Cu] J.J.M. Cuppen, *A Divide and Conquer Method for the Symmetric Tridiagonal Eigenproblem*, Numer. Math. 36, (1981) 177-195.
- [DS] J.J. Dongarra and D.C. Sorensen, *A Fully Parallel Algorithm for the Symmetric Eigenproblem*, SIAM J. Sci. Stat. Comput. 8, (1987) s139-s154.
- [Gr1] W.B. Gragg, *Positive Definite Toeplitz Matrices, the Arnoldi Process for Isometric Operators, and Gaussian Quadrature on the Unit Circle* (in Russian), in Numerical Methods in Linear Algebra, E.S. Nikolaev, ed., Moscow University Press, Moscow, 1982, pp. 16-32.
- [Gr2] W.B. Gragg, *The QR Algorithm for Unitary Hessenberg Matrices*, J. Comput. Appl. Math. 16, (1986) 1-8.
- [GH] W.B. Gragg and W.J. Harrod, *The Numerically Stable Reconstruction of Jacobi Matrices from Spectral Data*, Numer. Math. 44, (1984) 317-355.
- [GR1] W.B. Gragg and L. Reichel, *A Divide and Conquer Algorithm for the Unitary Eigenproblem*, in Hypercube Multiprocessors 1987, M.T. Heath, ed., SIAM, Philadelphia, 1987, pp. 639-647.
- [GR2] W.B. Gragg and L. Reichel, *A Divide and Conquer Method for the Unitary and Orthogonal Eigenproblems*, BSC Report 88/31, Bergen Scientific Centre, Bergen, 1988.

DISTRIBUTION LIST

DIRECTOR (2)
DEFENSE TECH. INFORMATION
CENTER, CAMERON STATION
ALEXANDRIA, VA 22314

DIRECTOR OF RESEARCH ADMIN.
CODE 012
NAVAL POSTGRADUATE SCHOOL
MONTEREY, CA 93943

LIBRARY (2)
CODE 0142
NAVAL POSTGRADUATE SCHOOL
MONTEREY, CA 93943

DEPARTMENT OF MATHEMATICS
CODE 53
NAVAL POSTGRADUATE SCHOOL
MONTEREY, CA 93943

CENTER FOR NAVAL ANALYSES
4401 FORD AVENUE
ALEXANDRIA, VA 22302-0268

PROFESSOR WILLIAM GRAGG (15)
CODE 53Gr
DEPARTMENT OF MATHEMATICS
NAVAL POSTGRADUATE SCHOOL
MONTEREY, CA 93943

NATIONAL SCIENCE FOUNDATION
WASHINGTON, D.C. 20550

DUDLEY KNOX LIBRARY



3 2768 00354737 3